

Enable PMLN7851A Bluetooth earpiece on TLK110

1 Choose WAVE Devices in the WAVE Admin menu and select the device you want to modify. (Click on the TLK110 that you want to modify in the overview)

2 Select Actions.

3 Select Bluetooth Accessories

Device Info

	Reported	Desired
Device Type	TLK100i	-
IMEI	354124100009653	-
Serial Number	341AVJ0244	-
Cellular Status	Activated	-

ATTENTION: If Bluetooth is not enabled, you must do this first under Settings and Menu Visibility.

MOTOROLA SOLUTIONS

Brightness Level 1

Device Mode user

Maintenance Mode PW -

Voice Announcements On

Location On

WiFi On

Cellular On

Bluetooth On

Scan Off

Do Not Disturb Off

Menu Visibility

← DATAMATIK DEMO		Device Info	
DATAMATIK TLK DEMO		Settings	
Users		Menu Visibility	
TalkGroups		Reported	Desired
WAVE Devices		Location <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Clone Devices		Alert Tones <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Voice Announcements <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Brightness Level <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Do Not Disturb <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		WiFi <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Cellular <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Bluetooth <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Scan <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
		Contacts <input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

When this is done, you can add Bluetooth accessory:

Up in the right corner, now select Bluetooth Accessories (Step 3)

You need to enter the name **EP910W_xxxx** and pin code **0000**. (xxxx = last 4 digits of the Bluetooth address. Use PC or Mobile phone to see the Bluetooth address.)

Name	MAC Address	Pin Code	Delete	Unpair	Edit
Silentex 3.3.5.2MW	886b0fe5225e	0000	Delete	Unpair	Edit
OCW_EARPIECE_PTT	001b41b24c22	0000	Delete	Unpair	Edit

Save the settings and the earpiece can be connected.

The PMLN7851 shall be set into LTE WaveOnCloud mode (see PMLN7851 manual for information)

Put the PMLN7851 in Pairing mode by pressing the MFB button for 5 – 6 seconds.

Turn off your radio Bluetooth function and turn on again.

Wait until you hear “your headset is connected”.

Then all is set and PMLN7851 works, including the PTT on the microphone boom.