## SAVOX

## SAVOX NOISE-COM 400 Ex Motorola ANC RSM

This version of SAVOX® Noise-COM 400 Ex is compatible with Ex-approved Motorola PMMN4093 and PMMN4094 ACN remote speaker microphones. Comes with dynamic boom microphone.

## Key Benefits:

- · Protects hearing (SNR 30 dB) · Ex approved can be used in potentially explosive environments like oil rigs
- · Replaceable mic and ear cushions
- Mounts easily into construction helmets (list of certified helmets from Sales)
- · Durable design



Market Segment	Industr
Housing Material	ABS
Weight (text)	375 g

 $\begin{array}{lll} \text{Operational Temperature Min} & -20 \, ^{\circ}\text{C} \, (-4 \, ^{\circ}\text{F}) \\ \text{Storage Temperature Min} & -20 \, ^{\circ}\text{C} \, (-4 \, ^{\circ}\text{F}) \\ \text{Protection Against Drop(fall)} & 2 \, \text{meters} \\ \text{Headset Connector} & \text{QR4 male} \\ \text{Cable Type} & \text{Coiled} \\ \text{Hearing Protector Certification} & \text{EN 352, US} \\ \text{Attachment/Fastening} & \text{Helmet mount} \end{array}$ 

Product code Housing Colour Options (text)

Operational Temperature Max Storage Temperature Max Microphone Type Connectivity Ex/IS Emergency Button

Hearing Protector Attenuation

K53692-3500

Blue
Helmet specific adapters for

most common helmets<br/>br/>When ordering, please inform the correct helmet model to be used with the headset

55 °C (131 °F) 60 °C (140 °F) Dynamic Wired ATEX / IECEX

No

SNR 30dB, according to EN352-3:2002<br/>br/>NRR 24dB, according to ANSI S3.19-1974